



# G1669BP

## High Performance Current Mode PWM Controller

### 1. General Description

G1669BP is a highly integrated Green Mode PWM control IC, It minimizes the component counts, circuit space, and reduces the overall material cost for the power applications.

The G1669BP features green-mode power-saving operation, auto gain control, and internal slope compensation, soft-start functions to optimized high performance, low standby power consumption and wide output voltage range PD adapter solutions.

At full loading, the IC operates in fixed frequency mode. When the loading goes low, it operates in Green mode with valley switching for high power conversion efficiency. When the load is very small, the IC operates in Extended Burst Mode to minimize the standby power loss. As a result, high conversion efficiency can be achieved in the whole loading range.

G1669BP offers complete protection coverage including cycle-by-cycle current limiting (OCP), over temperature protection (OTP), output short, output and VDD over voltage protection. Excellent EMI performance is achieved with proprietary frequency shuffling technique.

#### Applications

Offline AC/DC flyback converter for

- PD adapters
- Wide output range adapters
- Open Frame Switching Power Supply

#### Features

- ◆ Built-in High-Voltage Power MOS
- ◆ Ultra low operating current at light/no load
- ◆ Adaptive loop gain compensation
- ◆ Extended burst mode control for improved efficiency and low standby power
- ◆ Frequency Conversion Mode Operation with 65KHz or 45KHz fixed frequency @ Full Load
- ◆ Peak Load Mode with 125KHz max frequency
- ◆ Valley switching operation @ Green mode
- ◆ Internal OCP compensation for universal line voltage
- ◆ Power on soft start reducing MOSFET Vds stress
- ◆ Audio noise free operation
- ◆ Protection Features
  - VDD UV lockout and Over voltage protection
  - Cycle-by-Cycle over current protection with auto-recovery
  - Output over voltage protection with latch shut down
  - Secondary rectifier diode open and short circuit protection with auto-recovery
  - Secondary winding Open and short circuit protection with auto-recovery
  - Output short protection (SCP) with auto-recovery
  - Over temperature protection (OTP) with latch shut down
  - Overload protection (OLP) with auto-recovery
- ◆ Pb-free DIP7




# G1669BP

## High Performance Current Mode PWM Controller

### 2. Products Information

#### 2.1 Pin configuration



DIP8 Package

Fig.1. G1669BP Pin Configuration

Pin Name	I/O	Description
GND	P	Ground.
FB	I	Feedback input pin.By connecting an opto-coupler to close the control loop and achieve the regulation.
DEM	I	Multiple functions pin.Connecting a NTC resistor to ground for OTP detection.Connecting a resistor from Vaux can adjust IOVP/ISCP trigger current and detect transformer core demagnetization.If both OTP and OVP/SCP are needed,a diode should be connected between DEM pin and the NTC resistor.
CS	I	Current sense input,connect it to sense the MOSFET current.
VDD	P	Power Supply.
DRAIN	O	HV MOSFET Drain Pin. The Drain pin is connected to the primary lead of the transformer

#### 2.2 Series Description

Product	Package	85~264VAC output power	200~240VAC output power
G1669BP	DIP7	27W	33W

**Note:**Maximum practical continuous power in an Adapter design with sufficient drain pattern as a heat sink, at 40°C ambient. Higher output power is possible with extra added heat sink or air circulation to reduce thermal resistance.The recommended output power does not mean that this power can be made, which is determined by the actual ambient temperature and the actual shell size and whether the glue is filled.